

in.



AC Power Adapter

Belt Clip

Technical Specifications

- Channels: Four channels, isolated between channels
- Wave Form: Asymmetrical Biphasic Square Pulse
- Amplitude: 0-100 mA (peak to peak into 500 ohm load each channel)
- Output Voltage: 0 to 50V (500 ohm load)
- Modes: 5 TENS Modes: B (Burst), N (Normal), M (50% Modulated Rate & Width), S1 (40% Modulated Width), S2 (70% Modulated Width) 3 EMS Modes: C (Constant), S (Synchronous), A (Alternating)
- Pulse Rate (Frequency): 2 150 Hz, 1 Hz/step
- Pulse Width (Duration): 50 300 microseconds (us), 10 us/step
- Contraction (On) Time: 2 90 seconds, 1 sec/step
- Relaxation (Off) Time: 0 90 seconds, 1 sec/step
- Ramp Up/Down Time: 1 8 seconds, 1 sec/step (The "On" time will increase and decrease in the setting value)
- Two Adjustable Treatment Timers: From 1 to 60 minutes or Continuous. Adjustable in 1 min/step from 1 to 15 minutes, and 5 min/ step from 15 to 60 minutes. Treatment time countdown automatically.
- Compliance Usage Meter: Records up to 60 sessions, up to 999 hours
- Low Battery Indicator: Battery symbol appears when battery power is low
- · Power Supply: Four AA heavy duty batteries or AC adapter
- Size: 13.8cm(L) x 7.8cm(W) x 2.8cm(H)
- Weight: 425 grams with battery

Features

Four channel (8 lead) Digital Combo TENS / EMS Neuromuscular Stimulator

CH1

CH₂

Comfy 4

CH3

- Fully digital with micro-processor circuitry and controls
- 5 TENS Adjustable Modes (Normal, Burst, Modulated Rate & Width, Strength Duration 1, Strength Duration 2) 12 **TENS Preset Programs**
- 3 EMS Adjustable Modes (Constant, Synchronous, Alternating)12 EMS Preset Programs
- Large, easy-to-read LCD display that shows all parameters
- 2 seperate Treatment Timers for treating 2 areas at a time: 1-60 minutes, or Continuous operation
- Treatment Countdown display with Automatic Shut-Off
- Compliance Monitor records up to 999 hours of usage •
- AC adaptor (included) or 4AA battery power supply
- Low-battery indicator display
- Sturdy all-metal belt clip
- **3-year warranty**
- Comes with 2 pkgs of 4 reusable self-adhering electrodes, • 1 set 43" pin leadwires, 4 each AA heavy duty battery, AC Adaptor, carrying case, and instruction manual

Distributed by: